



R2C-AVR₁₀₀₈

Automatic voltage regulator with surge protection

IDEAL PROTECTION FOR




LED / LCD screens, Computer, Audio / Video, Entertainment, Video game console and more...

R2C-AVR¹⁰⁰⁸

Automatic voltage regulator with surge protection

The new and advanced R2C Automatic Voltage Regulator is the most complete and has the best component quality. It offers 8 outlets, corrects low and high voltages and filters against damaging electrical transients and power surges. Provides clean regulated energy 120VAC.



1. Regulation LED
2. Power LED
3. Coaxial protection
4. 4 with AVR Surge protection
5. 4 only with surge protection



MODEL		R2C-AVR 1008
Capacity		1000 VA/500W
Input	Voltage	120 Vac
	Frequency	50/60 Hz +/- 3%
	Voltage Range	92 Vac - 144Vac
	Max. Input Current (Bypass)	6A Max 720W
Output	Voltage	120 Vac
	Frequency	50 Hz - 60 Hz
	Voltage Range	120 Vac (116 ±12%)
	Number and type of outputs	4 Nema 5-15R with AVR and surge suppressor + 4 Nema 5-15R only with surge suppression
	Power Cord	Nema 5-15P 0.5mm 1M long
	Max. Input Current (Bypass)	500W (6A Max)
Protection	Overload	Breaker
	Shorted	Breaker
	Overheat Protection	Breaker
	Lightning Overload Protection(Joules)	175
LED	On / Off	Blue
	Regulation	Yellow
Physical	Dimension (Length x Height x Depth)	125 x 77 x 146 mm
	Weight (Kg)	1.11
Environment	Temperature	0 - 95% (not condensed)
	Acoustic Noise	<40 dBA @ 1 meter
Certifications		ISO 9001, ISO 14001, CIDET and NOM

"Specifications subject to change without notice"



Scan and know our products

Bolivia: 800-100156 **Colombia:** 01800-5181617 **Costa Rica:** 800-435237 **El Salvador:** 800-6773 **Honduras:** 1800-25616099
México: 001800 514 8611 **Panamá:** 011-00800-2268611 **Perú:** 0800-54674 **República Dominicana:** 1888-7514876 **Venezuela:** 0800-1627485